



RATIO (Ip / Is, (A))	BURDEN (VA) CI 1	BURDEN (VA) CI 0.5	ODERING CODE
1000/5A	7.5VA	5VA	JP-820-1000
1200/5A	7.5VA	5VA	JP-820-1200
1500/5A	10VA	7.5VA	JP-820-1500
1600/5A	10VA	7.5VA	JP-820-1600
2000/5A	10VA	7.5VA	JP-820-2000
2500/5A	15VA	10VA	JP-820-2500
3000/5A	15VA	10VA	JP-820-3000
3200/5A	15VA	10VA	JP-820-3200
4000/5A	20VA	15VA	JP-820-4000
5000/5A	20VA	15VA	JP-820-5000
6000/5A	20VA	15VA	JP-820-6000
6300/5A	25VA	20VA	JP-820-6300
7000/5A	25VA	20VA	JP-820-7000
8000/5A	30VA	25VA	JP-820-8000



Designed by Thanh Tài	Checked by Trọng Huân	Approved by Trọng Huân	Date 9/14/2022	Date 9/14/2022
ILEC Electrical		JP-820 Current Transformer		
		JP-820_1.0	Edition 1.0	Sheet 1 / 1